



Cisco Unity Express Commands: P

Last Updated: October 20, 2009

parameter (ccn application)

To set the value for a CCN application parameter, use the **parameter** command in Cisco Unity Express configuration application mode. This command does not have a **no** form.

parameter *parameter-name* "value"

Syntax Description	parameter-name	Specifies the parameter whose value is being set. These parameters are specified in the application script.
	"value"	Specifies the value for the parameter. The value must be entered within double quotes.

Command Modes Configuration application

Command History	Cisco Unity Express Version	Modification
	1.0	This command was introduced on the Cisco Unity Express network module and in Cisco Unified Communications Manager Express 3.0.
	1.1	This command was implemented on the advanced integration module (AIM) and in Cisco Unified Communications Manager 3.3(3).
	1.1.2	This command was implemented on the Cisco 2800 series and Cisco 3800 series routers.

Usage Guidelines Following are the parameters that may be configured for the aa.aef script:

- welcomePrompt—default: AAWelcome.wav
- operExtn—default: none

REVIEW DRAFT - CISCO CONFIDENTIAL

- holidayPrompt—default: AAHolidayPrompt.wav
- businessOpenPrompt—default: AABusinessOpen.wav
- businessClosedPrompt—default: AABusinessClosed.wav
- businessSchedule—default: systemschedule
- disconnectAfterMenu—default: false
- allowExternalTransfers—default: false

Following are the parameters that may be configured for the aa_simple.aef script:

- welcomePrompt—default: AAWelcome.wav
- operExtn—default: 0
- MaxRetry—default: 3
- holidayPrompt—default: AAHolidayPrompt.wav
- businessOpenPrompt—default: AABusinessOpen.wav
- businessClosedPrompt—default: AABusinessClosed.wav
- playExtensionsPrompt—default: AASPlayExtensions.wav
- extensionLength—default: 1
- businessSchedule—default: systemschedule
- disconnectAfterMenu—default: false
- allowExternalTransfers—default: false

Use the default parameter command to configure custom-defined parameters.

Examples

The following examples sets the value of the MaxRetry parameter to 6:

```
se-10-0-0-0# config t
se-10-0-0-0(config)# ccn application autoattendant
se-10-0-0-0(config-application)# parameter MaxRetry "6"
se-10-0-0-0(config-application)# end
se-10-0-0-0(config)# exit
```

Related Commands

Command	Description
ccn application	Configures the CCN applications, such as voice mail and auto attendant.
default (ccn application)	Configures application parameters.
show call-agent	Displays the CCN application details.

REVIEW DRAFT - CISCO CONFIDENTIAL**parameter (ccn subsystem edbs dbprofile)–IVR Only**

To specify the Java Database Connectivity (JDBC) driver–specific parameter for the Cisco Unity Express IVR enterprise database subsystem (EDBS), use the **parameter** command in Cisco Unity Express IVR EDBS profile configuration mode. To delete the JDBC parameter, use the **no** form of this command.

parameter *name value*

no parameter *name value*

Syntax Description	<i>name value</i> (Optional) Name value pair that matches the JDBC driver requirements.
---------------------------	---

Command Default	None
------------------------	------

Command Modes	Cisco Unity Express IVR EDBS profile configuration
----------------------	--

Command History	Cisco Unity Express Version	Modification
	3.0	This command was introduced.

Usage Guidelines	After the ccn subsystem edbs dbprofile command is successfully performed, use the optional parameter command to specify the JDBC driver–specific parameter. The name value pair must match the JDBC driver requirements. Each JDBC driver can have its own unique set of customized settings. You can use this command multiple times to set multiple driver properties.
-------------------------	--

Examples	The following example configures the JDBC driver parameters:
-----------------	--

```
se-10-0-0-0# config t
se-10-0-0-0(config)# ccn subsystem edbs dbprofile mydbprofile
Adding new Database profile
se-10-0-0-0(config-dbprof)# parameter *headerchar *continuation
se-10-0-0-0(config-dbprof)# end
se-10-0-0-0(config)# exit
```

Related Commands	Command	Description
	show ccn subsystem edbs dbprofile–IVR Only	Displays the Cisco Unity Express IVR EDBS configuration settings.

REVIEW DRAFT - CISCO CONFIDENTIAL

privilege

To add and configure a new privilege or define the properties of an existing privilege, use the **privilege** command in Cisco Unity Express configuration mode. Use the **no** version to remove the privilege.

```
privilege privilege-name [description string | operation operation-name | include
privilege-name2]
```

```
no privilege privilege-name
```

Syntax Description

<i>privilege-name</i>	Label used to identify and configure a new privilege.
description <i>string</i>	(Optional) Add a description for the privilege. The description appears in the output of the show privilege detail and show privileges commands.
operation <i>operation-name</i>	(Optional) Associate an operation to the privilege.
include <i>privilege-name 2</i>	(Optional) Include, or nest, another privilege into this privilege.

Defaults

If no new privileges are defined, only predefined privileges are available. Unless otherwise specified, the default for new privileges is that they have no operation associated with them, no text description, and no second privilege is nested within them.

Command Modes

Cisco Unity Express configuration (config)

Command History

Cisco Unity Express Version	Modification
7.0	This command was introduced.

Usage Guidelines

If no new privileges are added, predefined privileges are used.

Examples

The following example enables authentication for the console:

```
se-10-0-0-0# config t
se-10-0-0-0(config)# privilege sales_vp operation security.configuration
```

Related Commands

Command	Description
show operations	Shows all operations.
show privileges	Shows all system privileges.

REVIEW DRAFT - CISCO CONFIDENTIAL

purge notification (ccn reporting historical)

To configure e-mail addresses to notify users of automatic database purges of the Cisco Unity Express IVR reporting historical database, use the **purge notification** command in Cisco Unity Express IVR reporting historical configuration mode. Use the **no** form of this command to delete this configuration.

purge notification email address *email-address*

no purge notification email address *email-address*

Syntax Description	email address	E-mail address, or series of e-mail addresses (of up to 255 characters in length) separated by commas, sent to notify users that the reporting historical database has been purged.
	<i>email-address</i>	

Command Default No default e-mail address is configured.

Command Modes Cisco Unity Express IVR reporting historical configuration

Command History	Cisco Unity Express Version	Modification
	3.0	This command was introduced,

Usage Guidelines There is no default e-mail address for sending a notification. If an e-mail address is not configured, notifications are not sent.

If you must configure more than one e-mail address, enter the series of e-mail addresses separated by commas, without spaces.

Examples The following example configures an e-mail address to notify administrators that the Cisco Unity Express IVR reporting historical database has been automatically purged:

```
se-10-0-0-0# config t
se-10-0-0-0(config)# ccn reporting historical
se-10-0-0-0(config-hrdm)# purge notification email address name@domain.com
se-10-0-0-0(config-hrdm)# end
se-10-0-0-0(config)# exit
```

Related Commands	Command	Description
	show ccn reporting historical	Displays the Cisco Unity Express IVR reporting historical database configuration settings.

REVIEW DRAFT - CISCO CONFIDENTIAL

purge now (ccn reporting historical)

To manually purge the Cisco Unity Express IVR reporting historical database and remove historical data older than the configured *days-to-keep* number of days, use the **purge now** command in Cisco Unity Express IVR reporting historical configuration mode.

purge now *days-to-keep* *days*

Syntax Description	days-to-keep <i>days</i>	Number of days after which data older than the number of days specified are deleted from the reporting historical database. The valid range is from 1 to 1000.
---------------------------	---------------------------------	--

Command Default	None
------------------------	------

Command Modes	Cisco Unity Express IVR reporting historical configuration
----------------------	--

Command History	Cisco Unity Express Version	Modification
	3.0	This command was introduced,

Usage Guidelines	When the database is purged, historical statistics older than the configured <i>days-to-keep</i> value are removed from the database. The <i>days-to-keep</i> value is required for manually purging the database.
-------------------------	--

Examples	The following example manually purges the reporting historical database and any data older than 7 days:
-----------------	---

```
se-10-0-0-0# config t
se-10-0-0-0# ccn reporting historical
se-10-0-0-0(config-hrdm)# purge now days-to-keep 7
se-10-0-0-0(config-hrdm)# end
se-10-0-0-0(config)# exit
```

Related Commands	Command	Description
	show ccn reporting historical	Displays the Cisco Unity Express IVR reporting historical database configuration setting.

REVIEW DRAFT - CISCO CONFIDENTIAL

purge purge-capacity (ccn reporting historical)

To set the purge threshold (as a percentage of the total database capacity) and the age of data to be purged in the Cisco Unity Express IVR reporting historical database, use the **purge purge-capacity** command in Cisco Unity Express IVR reporting historical configuration mode. Use the **no** form of this command to set the purge capacity percentage and the *number-of-days* to purge to the default value.

purge purge-capacity percentage percent days-to-purge days

no purge purge-capacity percentage percent days-to-purge days

Syntax Description	percentage percent	days-to-purge days
	Purge threshold as a percentage of the total database capacity. The valid purge threshold percentage is in the range from 0 to 90.	Number of days after which data older than the number of days specified are deleted from the reporting historical database. The valid number of days-to-purge is in the range from 0 to 999.

Command Default
The default purge capacity percent value is 90.
The default number of *days* to purge is 7.

Command Modes
Cisco Unity Express IVR reporting historical configuration

Command History	Cisco Unity Express Version	Modification
	3.0	This command was introduced,

Usage Guidelines
The maximum purge capacity percentage value allowed is 90.

Examples
The following example configures the Cisco Unity Express IVR reporting historical database purge capacity threshold to 90 and the number of days-to-purge data to 7:

```
se-10-0-0-0# config t
se-10-0-0-0(config)# ccn reporting historical
se-10-0-0-0(config-hrdm)# purge purge-capacity percentage 90 days-to-purge 7
se-10-0-0-0(config-hrdm)# end
se-10-0-0-0(config)# exit
```

Related Commands	Command	Description
	show ccn reporting historical	Displays the Cisco Unity Express IVR reporting historical database configuration setting.

REVIEW DRAFT - CISCO CONFIDENTIAL

purge schedule (ccn reporting historical)

To schedule the time of day for daily purging the Cisco Unity Express IVR reporting historical database, use the **purge schedule** command in Cisco Unity Express IVR reporting historical configuration mode. Use the **no** form of this command to set the scheduled purge time and number of days to the default value.

purge schedule time *hh:mm* **days-to-keep** *days*

no purge schedule time *hh:mm* **days-to-keep** *days*

Syntax Description

time <i>hh:mm</i>	The daily time in hours and minutes (hh:mm) in 24-hour format, at which the data is purged from the reporting historical database.
days-to-keep <i>days</i>	Sets the number of days after which data older than the number of days specified are deleted from the reporting historical database. The value for days-to-keep is in the range from 0 to 1000.

Command Default

The default purge schedule is set at 04:00. The default number of days-to-keep is 90 for the AIM-CUE/AIM2-CUE module and 365 for the NM-CUE, NM-CUE-EC, NME-CUE and ISM-SRE-300-K9 modules.

Command Modes

Cisco Unity Express IVR reporting historical configuration

Command History

Cisco Unity Express Version	Modification
3.0	This command was introduced,

Usage Guidelines

Database purging is performed daily at the time of day (in hours:minutes 24-hour format) specified. Stored historical data older than that specified in the *days-to-keep* value (in days) is purged from the database. [Table 1](#) summarizes the maximum values that can be specified for *days-to-keep*.

Table 1 Maximum Days-to-Keep Value

Database	Storage Limits
AIM-CUE/AIM2-CUE	90 days or database 90% full
NM/NM-EC/NME-CUE ISM-SRE-300-K9 SM-SRE-700-K9	365 days or database 90% full

Examples

The following example configures the reporting historical database to purge data older than 30 days at 4:00 a.m. daily:

```
se-10-0-0-0# config t
se-10-0-0-0(config)# ccn reporting historical
se-10-0-0-0(config-hrdm)# purge schedule time 04:00 days-to-keep 30
se-10-0-0-0(config-hrdm)# end
```


REVIEW DRAFT - CISCO CONFIDENTIAL

```
se-10-0-0-0(config)# exit
```

Related Commands

Command	Description
show ccn reporting historical	Displays the Cisco Unity Express IVR reporting historical database configuration settings.

REVIEW DRAFT - CISCO CONFIDENTIAL**purge warning-capacity (ccn reporting historical)**

To send an e-mail notification when a certain percentage database capacity is reached, use the **purge warning-capacity** command in Cisco Unity Express IVR reporting historical configuration mode.

When the percentage of capacity is reached, an e-mail is sent to notify users that the Cisco Unity Express IVR reporting historical database capacity is approaching its limit. Use the **no** form of this command to set the warning capacity percentage to the default value.

purge warning-capacity percentage *percent*

no purge warning-capacity percentage *percent*

Syntax Description

percentage <i>percent</i>	Percentage of the total Cisco Unity Express IVR reporting historical database capacity. The valid percentage is in the range from 0 to 95.
----------------------------------	--

Command Default

The default is 85 percent of database capacity.

Command Modes

Cisco Unity Express IVR reporting historical configuration

Command History

Cisco Unity Express Version	Modification
3.0	This command was introduced,

Usage Guidelines

An e-mail warning is sent when the maximum percentage value (90 percent) is reached.

Examples

The following example configures the warning percentage for the Cisco Unity Express IVR reporting historical database at 80 percent:

```
se-10-0-0-0# config t
se-10-0-0-0(config)# ccn reporting historical
se-10-0-0-0(config-hrdm)# purge warning-capacity percentage 80
se-10-0-0-0(config-hrdm)# end
se-10-0-0-0(config)# exit
```

Related Commands

Command	Description
show ccn reporting historical	Displays the Cisco Unity Express IVR reporting historical database configuration settings.