# HP Laser MFP 136 Series

#### Laser MFP performance at an affordable price

Get productive MFP performance at an affordable price. Print, scan and copy, produce high-quality results, and print and scan from your phone.<sup>1,6</sup>







# Legendary quality, surprisingly affordable price

- This surprisingly small laser delivers exceptional quality, page after page.
- Produce sharp text, bold blacks and crisp graphics.
- Rely on a high-performance laser MFP at an affordable price.

	+	
		Ц
L	_	Ц
1		

#### Designed to fit your space

- You can fit this MFP almost anywhere it's that small and compact.
- Get print speeds up to 20 ppm (A4).<sup>2</sup>
- Get quick and easy printing directly at the control panel.
- Get versatile performance and print, scan, and copy.



# Easy mobile printing and scanning with HP Smart app<sup>6</sup>

- Get simple setup, and print and scan from your phone, with the HP Smart app.<sup>1,6</sup>
- Easily print from a variety of smartphones and tablets.<sup>3,6</sup>
- Easily share resources access and print with wireless networking.<sup>4,6</sup>
- Connect your smartphone or tablet directly to your printer – easily print without accessing a network.<sup>5,6</sup>

<sup>1</sup> Requires the HP Smart app download. For details on local printing requirements see <u>hp.com/go/mobileprinting</u>. <sup>2</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information, see <u>hp.com/go/printerclaims</u>. Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>3</sup> For details on local printing requirements see <u>hp.com/go/mobileprinting</u>. <sup>4</sup> Wireless operations are compatible with 2.4 GHz and 5.0 GHz operations only. Learn more at <u>hp.com/go/mobileprinting</u>. Wi-Fi is a registered trademark of Wi-Fi Alliance<sup>®</sup>. <sup>6</sup> Applicable to HP Laser MFP 136w/nw model only.

# Product walkaround

HP Laser MFP 136nw shown



# Series at a glance







	HP Laser MFP 136a	HP Laser MFP 136w	HP Laser MFP 136nw
Product number	4ZB85A	4ZB86A	4ZB87A
Function	Print, copy and scan	Print, copy, scan and wireless	Print, copy, scan and wireless
Memory / processor	128MB / 600MHz	128MB / 600MHz	128MB/600MHz
Control panel	2-Line LCD; 12 Buttons (Power, Cancel, Start, Navigation (Menu, OK, Back, Left, Right), ID Copy, Contrast, Scale, Info); LED indicator lights(Power, Status)	2-Line LCD; 12 Buttons (Power, Cancel, Start, Navigation (Menu, OK, Back, Left, Right), ID Copy, Contrast, Scan to, Wireless); LED indicator lights (Power, Status, Wireless)	2-Line LCD; 12 Buttons (Power, Cancel, Start, Navigation (Menu, OK, Back, Left, Right), ID Copy, Contrast, Scan to, Wireless); LED indicator lights (Power, Status, Wireless)
Mobile printing⁴	Not available	Apple AirPrint™; Google Cloud Print™; Mobile Apps; Mopria™ Certified; Wi-Fi® Direct Printing	Apple AirPrint™; Google Cloud Print™; Mobile Apps; Mopria™ Certified; Wi-Fi® Direct Printing
Connectivity	Hi-Speed USB 2.0 port	Hi-Speed USB 2.0; Wireless 802.11 b/g/n	Hi-Speed USB 2.0; Fast Ethernet 10/100Base-Tx network port; Wireless 802.11 b/g/n
Recommended monthly page volume	Up to 2,000 pages	Up to 2,000 pages	Up to 2,000 pages
Print speed	Up to 20 ppm (A4)	Up to 20 ppm (A4)	Up to 20 ppm (A4)

<sup>1</sup> Requires the HP Smart app download. For details on local printing requirements, see <u>hp.com/go/mobileprinting</u>.<sup>2</sup> Excludes first set of ISO test pages. For details, see <u>hp.com/go/printerclaims</u>.<sup>3</sup> Wireless performance is dependent upon physical environment and distance from access point and may be limited during active VPN connections.<sup>4</sup> May require a firmware upgrade to be compatible, download at <u>hp.com/go/support</u> <sup>5</sup> Applicable for HP Laser MFP 136w/nw model only.

### **HP** Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. Choose from:

#### Optimized Care (optimum performance

and stability): 4 hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

#### Standard Care (high level of uptime):

Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

Basic Care (minimum recommended support): Next Business Day Onsite Support

4 hour Onsite Support: Onsite support within four hours after a service call received within the coverage window

Next Business Day Onsite Support:

Onsite service the next business day after the service call is received

Maintenance Kit Replacement Service: Onsite replacement of your printer's

maintenance kit including parts, materials, and labor

### Installation with Network Configuration

Service: Assembly, network configuration, and basic administrator familiarization. For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit hp.com/go/printservices





### **Top Features**

This surprisingly small laser delivers exceptional quality, page after page.

Produce sharp text, bold blacks and crisp graphics.

Rely on a high-performance laser MFP at an affordable price.

Get simple setup, and print and scan from your phone, with the HP Smart app.<sup>1,6</sup>

Easily print from a variety of smartphones and tablets.<sup>2,6</sup>

Easily share resources – access and print with wireless networking.<sup>3,6</sup>

Connect your smartphone or tablet directly to your printer – and easily print without accessing a network.5,6

Get print speeds up to 20 ppm.<sup>4</sup>

Get quick and easy printing directly at the control panel.

Get versatile performance and print, scan, and copy.

Product			
4ZB85A	HP Laser MFP 136a	HP Laser MFP 136a	
4ZB86A	HP Laser MFP 136w		
4ZB87A	HP Laser MFP 136nw		
Replacemer	nt Cartridges <sup>7</sup>		
W1110A	HP 110A Black Original Laser Toner Cartridge (~1,500 pages) - China Only		
W1112A	HP 110A Black Original Laser Toner Cartridge (~1,500 pages) - India Only		
HP Care Pac	ks		
UB4V5E	HP 3-year Onsite Exchange Laser 13x MFP SVC		
UB4V8E	HP 3-year Next Business Day Exchange Laser 13x MFP SVC		
UB4W1E	HP 3-year Standard Exchange Laser 13x MFP SVC		
UB4W4E	HP 3-year Return to Depot Laser 13x MFP SVC		
,	investment with HP Care Pack. Let tails on HP Care Pack, go to <u>hp.con</u>	t HP certified engineers resolve your technical issues. n/go/cpc	
Hewlett-Pa	kard offices		
China	(010) 6564 3888	hp.com.cn	
India	(80) 2612 9000	hp.com/in	
Recommend	led Papers <sup>8</sup>		
CG964A	HP Professional Laser Paper, Glossy, A4, 250 sheets, 120 gsm		
CG965A	HP Professional Laser Paper, Glossy, A4, 150 sheets, 150 gsm		

CG964A CG965A CG966A	HP Professional Laser Paper, Glossy, A4, 250 sheets, 120 gsm HP Professional Laser Paper, Glossy, A4, 150 sheets, 150 gsm HP Professional Laser Photo Paper, Glossy, A4, 100 sheets, 200 gsm	
Q6550A	HP Professional Laser Photo Paper, Matte, A4, 100 sheets	
Please visit <u>hp.com/apac/paper</u> for more details		

#### HP Order-a-Cartridge<sup>8</sup>

Call HP's Order-a-Cartridge<sup>8</sup> service and have them conveniently delivered to your doorstep. China 800 820 0851/400 820 0851 India 1800 3003 3003

<sup>1</sup> Requires the HP Smart app download. For details on local printing requirements see <u>hp.com/go/mobileprinting</u>. <sup>2</sup> For details on local printing requirements see <u>hp.com/go/mobileprinting</u>. <sup>3</sup> Wireless operations are compatible with 2.4 GHz and 5.0 GHz operations only. Learn more at <u>hp.com/go/mobileprinting</u>. Wi-Fi is a registered trademark of Wi-Fi Alliance<sup>®</sup>. <sup>4</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information, see <u>hp.com/go/printerclaims</u>. Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>5</sup> Mobile device needs to be connected to Wi-Fi Direct<sup>®</sup> signal of a Wi-Fi Direct-supported AiO or printer prior to printing. Details at <u>hp.com/go/mobileprinting</u>. Wi-Fi Direct<sup>®</sup> is a registered trademark of Wi-Fi Alliance<sup>®</sup>. <sup>6</sup> Applicable to HP Laser MFP 135w model only. <sup>1</sup> Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <u>hp.com/go/learnaboutsupplies</u>. <sup>8</sup> Available in selected countries only

# **Technical specifications**

Model	HP Laser MFP 136a (4ZB85A)	HP Laser MFP 136w (4ZB86A)	HP Laser MFP 136nw (4ZB87A)	
Number of user		1–5 Users		
Functions	Print, copy, scan	Print, copy, sc	an and wireless	
Print	.,			
Technology		Laser		
Speed <sup>1</sup>		Black (normal, A4): Up to 20 ppm		
Duplex print options		Manual (driver support provided)		
First page out <sup>2</sup>	Plack (A4 readu)	As fast as 8.3 seconds; <b>Black (A4, sleep):</b> As fast as 1	9 soconds (15 min)	
Resolution	Black	best): Up to 1,200 x 1,200 dpi; Black (normal): 600 x	600 dhi	
Cartridges number		1 (black)		
Standard print languages		SPL		
Scan				
Туре		Flatbed		
Technology		Contact Image Sensor (CIS)		
Resolution	Hardware: Up to 4800	) x 4800 dpi; <b>Optical:</b> Up to 600 x 600 dpi; <b>Enhanced:</b>	Up to 4800 × 4800 dpi	
Max scanning size		Flatbed: 216 x 297 mm		
Grayscale levels		256		
Bit depth		8-bit (mono); 16-bit (colour)		
File format	Wind	ows Scan SW supports file format: PDF, JPG, TIFF, PNG	, BMP	
Input modes	Front-pane	el copy, HP MFP scan software, user application via TV	VAIN or WIA	
Scanner advanced features	Scan to WSD (network support only); Book Scanning; Poster Stitching for multiple scan; Text Converting; Scan to E-Book; Existing File to E-Book			
Twain version		Version 1.9		
Сору				
Speed <sup>3</sup>		Black (normal, A4): Up to 20 cpm		
First copy out	Black (A4): As fast as 8.9 seconds; Black (A4, sleep): As fast as 17 seconds (15 min)			
Max copies		Up to 99 copies		
Copier reduce/enlarge				
	25 to 400%		and Adjust Packground: Auto Fit Conu	
Copier setting	Copies; Original Size; Reduce/Enlarge; Darkness; Original Type; Collation; 2-Up; 4-Up; ID Copy; Adjust Background; Auto Fit Copy Automatic adjusting background; Extended layout (2-up, 4-up, ID copy); expanded contrast adjustments (11 different settings); Scale from one paper size to			
Copier smart software features	Automatic adjusting background; Extended layout (	another (Letter>A4, AutoFit)	(11 different settings);Scale from one paper size to	
Display	2-Line LCD (16 characters per line)			
Control panel	2-Line LCD; 12 Buttons (Power, Cancel, Start, Navigation (Menu, OK, Back, Left, Right), ID Copy, Contrast, Scale, Info); LED indicator lights (Power, Status)	2-Line LCD; 12 Buttons (Power, Cancel, Start, Navigation (Menu, OK, Back, Left, Right), ID Copy, Contras y, Scan to, Wireless); LED indicator lights (Power, Status, Wireless)		
Duty cycle (monthly, A4) <sup>4</sup>		Up to 10,000 pages		
Recommended monthly		100 to 2,000 pages		
page volume⁵				
Media				
Sizes (Supported)		A4; A5; A5(LEF); B5 (JIS); Oficio; Envelope (DL, C5)		
Weight (Supported)		60 to 163 g/m <sup>2</sup>		
Types	Plain. Thick. Thin. Cot	ton, Colour, Preprinted, Recycled, Labels, CardStock, B	lond. Archive. Envelope	
Paper handling		put: 150-sheet input tray; <b>Output:</b> 100-sheet output		
Memory				
Processor speed	Standard/Maximum: 128 MB			
Operating system compatibility	600 MHz Windows®: 7 (32/64 bit), 2008 Server R2, 8 (32/64 bit), 8.1 (32/64 bit), 10 (32/64 bit), 2012 Server, 2016 Server			
Minimum system	PC: Windows 7 or newer, Intel® Pentium® IV 1 GHz 32-bit or 64-bit processor or higher, 1 GB RAM, 16 GB HDD			
Connectivity				
Connectivity (standard)	Hi-Speed USB 2.0	Hi-Speed USB 2.0; Wireless 802.11 b/g/n	Hi-Speed USB 2.0; Fast Ethernet 10/100Base-Tx network port; Wireless 802.11 b/g/n	
Wireless capability	Not available	Ves huilt-in W	i-Fi 802.11b/g/n	
Mobile printing	Not available		-	
capability <sup>6</sup>		Apple AirPrint™; Google Cloud Print™; Mobile Apps; Mopria™ Certified; Wi-Fi® Direct Printing		
Supported network protocols	Not available	Via built-in networking solution: TCP/IP, IPv4, IPv6; print: TCP-IP port 9100 Direct Mode, LPD (raw queue support only), WSD; discovery: SLP, Bonjour, WS-Discovery; IP Config: IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Stateful via DHCPv6); management: SNMPv1/v2/v3, HTTP		
Security management	Not available	Password-protected network embedded Web server; enable/disable Network ports; SNMPv1 community password change; SNMPV2&V3 IPSec; Filtering : MAC, IPv4, IPv6		
Environmental				
Acoustics	Acoustic power emissions (active, printing):	Acoustic power emissions (active, printing): 6.5 B(A) (printing at 20 ppm); Acoustic power emissions (active scan): 6.25 B(A) (only 20 ipm ADF)		
Operating environment	Operating temperature range: 10 to 30° C; Recommended operating temperature: 15 to 27° C; Operating humidity range: 10 to 80% RH (non-condensing); Recommended operating humidity range: 20 to 70% RH (non-condensing); Storage temperature range: -20 to 40° C			
Energy savings feature technology		HP Auto-Off Technology; Power save		

## **Technical specifications**

Model	HP Laser MFP 136a (4ZB85A)	HP Laser MFP 136w (4ZB86A)	HP Laser MFP 136nw (4ZB87A)
Power specifications	Power supply type: Internal (Built-in) power supply; Power supply required: 110-volt input voltage: 110 to 127 VAC, 50/60Hz and 220-volt input voltage: 220 to 240 VAC, 50/60Hz; Power consumption: <sup>7</sup> Active Printing: 300 watts, Ready: 38 watts, Sleep: 1.9 watts, Manual off: 0.2 watts, Auto off/Manual on: 0.2 watts; Typical electricity consumption (TEC): <sup>8</sup> 0.876 kWh/Week (BA), 0.924 kWh/Week (ES)		
Dimension (W x D x H) <sup>9</sup>	406 x 359.6 x 253 mm		
Weight <sup>10</sup>	7.46 kg		
Warranty	One-year limited hardware warranty; For more info please visit us at support.hp.com		
What's in the box <sup>11</sup>	HP Laser MFP 136a; Preinstalled introductory HP Laser Jet Black print cartridges (~1.5K pages, CH/IN); Setup Guide; Reference Guide; Regulatory Statements Flyer; Power cord; USB cable	HP Laser MFP 136w; Preinstalled introductory HP Laser Jet Black print cartridges (~1.5K pages, CH/IN); Setup Guide; Reference Guide; Regulatory Statements Flyer; Power cord; USB cable	HP Laser MFP 136nw; Preinstalled introductory HP Laser Jet Black print cartridges (~1.5K pages, CH/IN); Setup Guide; Reference Guide; Regulatory Statements Flyer; Power cord; USB cable

<sup>1</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see <u>hp.com/go/printerclaims</u>, Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>3</sup> First Copy Out and Copy Speed measured using ISO/IEC 17629. For more information see <u>hp.com/go/printerclaims</u>, Exact speed varies depending on the system configuration, driver, and document complexity. <sup>4</sup> First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see <u>hp.com/go/printerclaims</u>, Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>6</sup> Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP Laserlet or HP Clor Laserlet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups. <sup>6</sup> HP recommends that the number of printer bages per month of based to measurement the value provides a to the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Pereduct warranty. Prequire a firmware upgrade to measurement of 1151/ device <sup>8</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 1150 device <sup>8</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 1150 device and 230V for Blue Angel. <sup>6</sup> Dimensions vary as per configuration <sup>10</sup> Weight varies as per configuration <sup>11</sup> Introductory cartridge sincluded; yields 1,500 black pages. Replacement cartridge average declare

#### To learn more, visit hp.com

© 2019 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. To the extent allowed by law, HP shall not be liable for technical or editorial errors or omissions contained herein.



Microsoft and Windows are registered trademarks of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.